

XS-12P-X2G2-X8G3-SFF Multi camera platform

- XIMEA Accessories
 - Technical Manual •
 - Version v251013 •

Introductions

About this manual

Dear customer.

Thank you for purchasing a product from XIMEA.

We hope that this manual can answer your questions, but should you have any further queries or if you wish to claim a service or warranty case, please contact your local dealer or refer to XIMEA Support on our website: www.ximea.com/support

The purpose of this document is to provide a description of XIMEA Accessories and to describe the correct way to install related software, drivers and run it successfully. Please read this manual thoroughly before operating your new XIMEA Accessories for the first time. Please follow all instructions and observe the warnings.

This document is subject to change without notice.

About XIMEA

XIMEA is one of the worldwide leaders for innovative camera solutions with a 30-year history of research, development and production of digital image acquisition systems. Based in Slovakia, Germany and the US, with a global distributor network, XIMEA offers their cameras worldwide. In close collaboration with customers XIMEA has developed a broad spectrum of technologies and cutting-edge, highly competitive products.

XIMEA's camera centric technology portfolio comprises a broad spectrum of digital technologies, from data interfaces such as USB 2.0, USB 3.1 and PCle to cooled digital cameras with CCD, CMOS and sCMOS sensors, as well as X-ray cameras.

XIMEA has three divisions – generic machine vision and integrated vision systems, scientific imaging and OEM/custom.

Our broad portfolio of cameras includes thermally stabilized astronomy and x-ray cameras, as well as specialty cameras for medical applications, research, surveillance and defense.

Slovakia

Contact XIMEA

XIMEA is a worldwide operating company

Headquarters, Sales worldwide Sales America R&D, Production

XIMEA GmbH XIMEA Corp. XIMEA s.r.o.

Am Mittelhafen 16 12600 W Colfax Ave., Suite A-130 Lesná 52 48155 Münster Lakewood, CO 80215 900 33 Marianka

Germany USA

Tel: +49 (251) 202 408-0 Tel: +1 (303) 389-9838 Tel: +421 (2) 205 104 26 Fax: +49 (251) 202 408-99 Fax: +1 (303) 202-6350 Fax: +421 (2) 205 104 27

Web www.ximea.com
General inquiries info@ximea.com
Sales sales@ximea.com
Support XIMEA Support

Contents

	About	XIMEA .	ual	2 2 2
1			ption	4
2			rawings	5
3			9	6
•			ches	6
4			of connectors	7 7
			erfaces	8
		4.2.1	Flex cable connector (24 pin)	8
		4.2.2	Flex cable connector (15 pin)	
		4.2.3	USB 3.1 Gen1 Type-A	
		4.2.4 4.2.5	Power connector	
_				
5		-	Popular gunnily	
			power supplyrequirement	
			nization mode selection	
			juration	
		5.4.1	Trigger input configuration	
		5.4.2	Trigger output configuration	
	5.5	Signal le	vel	
		5.5.1	ISO_GPI signal level	15
		5.5.2	ISO_GPO signal level	15
		5.5.3	ISO_GPO_5V0 signal level	15
6	Usage	s		16
	6.1	Buttons		16
		6.1.1	Trigger button	
		6.1.2	PCle reset button	16
7	Addition	onal info	rmation	17
8	Quicks	start guid	de	18
		-	e setup	
		8.1.1	Essential components	18
		8.1.2	Connecting the components	18
List	of figu	ıres		19
Liet	of tah	loc		ാറ

1 General description



Figure 1: Isometric view of XS-12P-X2G2-X8G3-SFF

The xiSwitch XS-12P-X2G2-X8G3-SFF is a multi-camera platform designed for high-performance synchronization of up to 12 cameras equipped with PCle connectors from xiX family.

The xiSwitch XS-12P-X2G2-X8G3-SFF features:

- Device ports: 12x PCle X2G2 Flex connectors with 10 Gbit bandwidth each for camera connections
- Device ports: 4x USB 3 X2G2 Flex connectors with 10 Gbit bandwidth each for camera connections
- 4x USB 3 Type-A connectors with 5 Gbit bandwidth
- Host ports: 2x PCle x4 Gen3 SFF MiniSAS HD connectors with output bandwidth of 64 Gbit
- External power for reliable operation of connected cameras
- Communication, control, and synchronization through IO connector

The power supply operates with a DC voltage range of 12 to 24 V.

The PCIe xSwitch accessories kit (ACC-XSWITCH-PCIE) is delivered together with the xSwitch. The kit contains CBL-10-01096 (power cable), MECH-SCRDRW-2.5MM-50MM screwdriver, and one CONN-5P-1847084 connector for GPIO purposes.

The xiSwitch XS-12P-X2G2-X8G3-SFF is designed for a wide range of applications, including:

360 panorama, Augmented or Virtual Reality (AR, VR), Autonomous self-driving vehicles, Street/city mapping, Deep learning tasks, Stereo camera systems, 3D scanning, Entertainment, Photogrammetry, FACS scanning, Face and Motion capture, UAV / UAS (drones), Cinematography, Videogrammetry and more.

2 Dimensional drawings




Figure 2: Dimensional drawing of XS-12P-X2G2-X8G3-SFF

Width [W]	Height [H]	Depth [D]	Mass [M]
140 mm	99.5 mm	38 mm	399.2 g

Table 1: Parameters and mass of XS-12P-X2G2-X8G3-SFF

3 Configuration

3.1 DIP switches

The numbering of the camera ports correspond to the number of the respective GPI and GPO dip switches.

The DIP switches have annotation on their body. The description of DIP switches (GPI, GPO) is written directly on the PCB top layer.




Figure 3: XS-12P-X2G2-X8G3-SFF DIP switches

The switch to select the synchronization mode is in the left bottom area, next to the annotation "GPI Sel" with two possible states - "GPI" and "GPO_5V". For more information see Section IO-subsystem..

4 Connectors

4.1 Location of connectors




Figure 4: Connectors location

Name	Description
USB-A 1-4	USB3 Type-A USB 3.0 (USB 3.1 Gen 1, Superspeed)
USB FL1-FL4	FPC/FFC USB Flex connectors
FL1-FL12	PCIe MX-X2G2 Flex connectors
10	5-pin IO connector, 1843826
SFF A	PCle iPass+ HD connector, SFF-8644, connector A
SFF B	PCle iPass+ HD connector, SFF-8644, connector B
PWR	3-pin Power input connector, 1843800

Table 2: Connectors description

4.2 Data interfaces

4.2.1 Flex cable connector (24 pin)

Item	Value
Connector	Molex 502244-2430 (-FL), Molex 502231-2400 (-FV)
Signals	PCle x2 Gen2, GND, IO
Mating Connectors	CBL-MX-X2G2-0M07 (-0M10,-0M25), CBL-PCIEFLEX-X2G2-0M10 (-0M25,-0M50)

Table 3: Flex connector description (24 pin)




Figure 5: Flex cable connector pinnout (24 pin)

Pin	Name	GPI/GPO index API	Туре
1	OUT1	-/1	Optically isolated Digital Output (OUT)
2	IN_OUT_GND	None	Common ground for opto-isolated IO
3	IN1	1/-	Optically isolated Digital Input (IN)
4	INOUT2	3/3	Non-isolated digital lines - Digital Input-Output (INOUT)
5	INOUT1	2/2	Non-isolated digital lines - Digital Input-Output (INOUT)
6	PWR	None	Power input
7	PWR	None	Power input
8	PCIe_RSTO_N_IN	None	PCle reset
9	GND	None	Ground return
10	PCle_PERN_0	None	PCle RX differential pair 0, neg.
11	PCle_PERP_0	None	PCle RX differential pair 0, pos.
12	GND	None	Ground return
13	PCle_PERN_1	None	PCle RX differential pair 1, neg.
14	PCle_PERP_1	None	PCle RX differential pair 1, pos.
15	GND	None	Ground return
16	PCIe_PETN_0	None	PCle TX differential pair 0, neg.
17	PCle_PETP_0	None	PCle TX differential pair 0, pos.
18	GND	None	Ground return
19	PCIe_PETN_1	None	PCle TX differential pair 1, neg.
20	PCle_PETP_1	None	PCle TX differential pair 1, pos.
21	GND	None	Ground return
22	PCIe_REFCLK_N	None	PCle reference clock diff. pair, neg.
23	PCIe_REFCLK_P	None	PCle reference clock diff. pair, pos.
24	GND	None	Ground return

Table 4: Flex connector 24 pin assignment

4.2.2 Flex cable connector (15 pin)

Item	Value
Connector	Molex 502244-15300 (-FL), Molex 502231-1500 (-FV)
Signals	USB 3.1 Gen1, IO, GND
Mating Connectors	CBL-MQ-FL-0M1, CBL-MQ-FL-0M25, CBL-USB3FLEX-0M10, CBL-USB3FLEX-0M25, CBL-USB3FLEX-0M50

Table 5: Flex connector description (15 pin)




Figure 6: Flex cable connector pinnout (15 pin)

Pin	Name	GPI/GPO index API	Туре
1	GND	None	Ground for pwr. and SuperSpeed signal return
2	SSRX-	None	SuperSpeed receiver differential pair
3	SSRX+	None	SuperSpeed receiver differential pair
4	GND	None	Ground for pwr. and SuperSpeed signal return
5	SSTX+	None	SuperSpeed transmitter differential pair
6	SSTX-	None	SuperSpeed transmitter differential pair
7	GND	None	Ground for pwr. and SuperSpeed signal return
8	D+	None	USB 2.0 differential pair
9	D-	None	USB 2.0 differential pair
10	GND	None	Ground for pwr. and SuperSpeed signal return
11	VBUS	None	Power input
12	VBUS	None	Power input
13	OUT1	-/1	Optically isolated Digital Output (OUT)
14	IN/OUT GND	None	Common pole (IO Ground)
15	IN1	1/-	Optically isolated Digital Input (IN)
Gnd. pins	SGND	None	Shield of FPC cbl. connected to shield of host controller

Table 6: Flex connector 15 pin assignment

Item	Value
Connector	USB 3.1
Signals	Standard USB 3.1 Gen1 Type-A Connector
Mating Connectors	Standard USB 3.1 Type-A Connector

Table 7: USB Type-A connector general description




Figure 7: USB3 Type-A pinout

Pin	Signal	Description
1	VBUS	Power supply 5 V
2	D-	USB 2.0 differential data line neg.
3	D+	USB 2.0 differential data line pos.
4	GND	Ground return for power and signal
5	SSRX-	SuperSpeed receive differential pair neg.
6	SSRX+	SuperSpeed receive differential pair pos.
7	GND	Ground return for power and signal
8	SSTX-	SuperSpeed transmit differential pair neg.
9	SSTX+	SuperSpeed transmit differential pair pos.

Table 8: USB Type-A pin assignment

4.2.4 Power connector

Item	Value
Connector	CONN Header Block 3-POS, 3.5MM, Right Angle, 250V/8A, THT, 1843800
Signals	Power, GND
Mating connector	Phoenix Contact 1847068 (CBL-10-01096) ¹

¹Power cable is part of the ACC-XSWITCH-PCIE kit

Table 9: Power connector description




Figure 8: Power connector pinout

Pin	Name	Description
1	Vin 12 to 24 V	Power 12 to 24 V
2	SHLD	Shielding
3	GND	Power supply Ground

Table 10: Power connector pin assigment

Item	Value
Connector	CONN Header Block 5-POS, 3.5MM, Right Angle, 250V/8A, THT, 1843826
Signals	IO, GND
Mating connector	Phoenix Contact 1847084 or 1863330

Table 11: IO connector general description




Figure 9: IO connector pinout

Pin	Name	Description
1	ISO_GPO	Open collector output from the selected "master" camera
2	ISO_GPO_5V	Push-pull 5 V output from the selected "master" camera
3	ISO_GND	(common) Isolated Ground for the IO subsystem
4	ISO_GPI	External input trigger signal, 3.3 to 24 V input
5	ISO_5V0	Isolated 5 V power output for IO subsystem ¹

 $^{^1\}mbox{Do}$ not connect external power supply to this pin. Sourcing capability limited to 5 V 400 mA, including power needed for IO subsystem.

Table 12: IO connector pin assigment

5 IO-subsystem

The IO subsystem is designed to enable synchronized operation of connected XIMEA cameras. Synchronization can be achieved either through an external trigger signal or by using a master-slave configuration. An external trigger signal is connected to the input pin ISO_GPI. In the master-slave mode, one of the cameras connected to the switch is designated as the master, while the remaining cameras are synchronized using the output signal from the master camera.

5.1 Internal power supply

To enable synchronization of all connected cameras via either an external trigger or the master camera's output, the switches include an internal 5 V power supply (an isolated 2 W DC/DC converter) that powers the IO subsystem.




Figure 10: Power supply of IO-subsystem

5.2 Circuitry requirement

All components of the IO subsystem are powered by the two voltage levels: ISO_5VO and ISO_GND. ISO_5VO is generated by the internal power supply.

5.3 Synchronization mode selection

Two synchronization modes are available:

- External trigger
- Master-slave mode

The selection between both modes is made via the dip-switch GPI-Select:




Figure 11: Synchronization mode selector

Position GPI-Sel	Synchronization mode
GPI	External trigger (pin ISO_GPI signal)
GP0_5V0	Master-Slave-Mode (pin ISO_GPO_5V signal)

Table 13: DIP switch mode description

5.4 IO configuration

The xSWITCH is designed to support different synchronization modes of the connected XIMEA cameras.




Figure 12: Functional diagram of the IO-system

The interconnected IO ports of the cameras are the optically isolated input and output lines.

5.4.1 Trigger input configuration

To synchronize the cameras, either the IO connector pin ISO_GPI (for external trigger mode) or the internal signal ISO_GPO_5V0 (for master-slave mode) is connected to the GPI pins of the cameras that require synchronization. The specific cameras to be synchronized are defined by configuring their individual DIP switches (GPI USB Camera n or GPI PCIe Camera n). These DIP switches connect the input signal to the corresponding camera's input line.

5.4.2 Trigger output configuration

One camera can be selected — and only one should be selected — to generate the output signal by configuring its specific DIP switch (GPO USB Camera n or GPO PCle Camera n). This output signal can be used to:

- Trigger all cameras connected to the same switch
- Trigger external devices (e.g., another xSWITCH)

The selected output signal will be connected to the internal and external signal ISO GPO / ISO GPO 5VO.

5.5 Signal level

5.5.1 ISO_GPI signal level

The signal level of the GPI is described in the following table:

V-in-min [V]	V-in-max [V]	State
0	< 0.4	Off (0)
0.4	2.5	Transient
>2.5	24	On (1)

Table 14: Digital trigger input ISO_GPI, signal levels

Note: The Input level V-in represents the amplitude of the input signal. Voltage levels referenced to common ground ISO_GND

5.5.2 ISO_GPO signal level

The digital output ISO_GPO type is Open Collector NPN, the maximum usable open circuit voltage level is 24 V.

5.5.3 ISO_GPO_5VO signal level

The signal level of the ISO_GPO_5VO is described in the following table:

Logic status	V-out [V]
Off (0)	0.0
On (1)	5.0

Table 15: Digital output ISO_GPO_5VO, signal levels

Note: The Output level V-out represents the amplitude of the input signal. The voltage levels refer to ISO_GND

6 Usages

6.1 Buttons

Two buttons are soldered on the multicamera platform.

6.1.1 Trigger button

This button can be used to generate a trigger pulse on the GPI-Selector output position to test the GPI configuration. A rising edge trigger pulse (0 V -> 5 V) will be generated.




Figure 13: trigger button

6.1.2 PCle reset button

Pressing this button will result in reset of the xiSwitch PCle bus and all connected cameras.




Figure 14: PCle reset button

Note: For debugging purposes only.

7 Additional information

Flex connectors are equipped with a locking mechanism. When locked, pulling the cable may lead to damage to the connector or the camera. When manipulating the cable, the power supply for the camera must be turned off.

Cables CBL-MQ-FL-xxx and CBL-MX-X2G2-xxxx have marked ends. It is important to connect the end marked "CAM" to the camera and the end marked "BOB" to the host or adapter (In this case to the xiSwitch XS-12P-X2G2-X8G3-SFF). Swapped orientation can cause damage to the camera.

Note: Flex cables PN: CBL-USB3FLEX-xxx or CBL-PCIEFLEX-X2G2-xxx are not polarized therefore the orientation of the cable between camera and host is not important.

Inserting Flex cable

- Step 1. Open the lock on the connecto.r
- Step 2. Insert the flex cable (e.g., CBL-MQ-FL-OM1) into the camera or xiSwitch.
- Step 3. Close the connector lock.

Detaching Flex cable

- Step 1. Open the lock on the connector.
- Step 2. Gently pull the cable in the marked direction.
- Step 3. Close the connector lock.




Figure 15: Flex cable inserting (left) / detaching (right)

8 Quickstart guide

8.1 Hardware setup

8.1.1 Essential components

It is important that the power is turned off when inserting/detaching the cables. General ESD precautions need to be applied. Failing this requirement may lead to camera and / or switch damage.

- XS-12P-X2G2-FF-X8G3-SFF multi camera platform
- Power cable CBL-10-01096
- Camera cables: e.g USB Flex cable (CBL-USB3FLEX-0M10), PCle Flex cable (CBL-MX-X2G2-0M25)
- XIMEA camera with PCle Flex or USB Flex interface
- Host cable: SFF-8644 cable (CBL-SFF-X4G3-10M0, CBL-SFF-X4G3-COP-1M0)
- Host PC (with SFF host adapter card)

8.1.2 Connecting the components

- Step 1. Ensure the power supply and the computer are turned off before connecting any cables. The order of cable connections is not strictly specified.
- Step 2. After all other cables are connected, connect the XS-12P-X2G2-FF-X8G3-SFF to the power supply.
- Step 3. Power on the computer.




Figure 16: XS-12P-X2G2-X8G3-SFF cable connection

List of Figures

1	Isometric view of XS-12P-X2G2-X8G3-SFF	
2	Dimensional drawing of XS-12P-X2G2-X8G3-SFF	5
3	XS-12P-X2G2-X8G3-SFF DIP switches	6
4	Connectors location	7
5	Flex cable connector pinnout (24 pin)	8
6	Flex cable connector pinnout (15 pin)	9
7	USB3 Type-A pinout Power connector pinout	10
8		
9	IO connector pinout	12
10	Power supply of IO-subsystem	13
11	Synchronization mode selector	13
12	Functional diagram of the IO-system	14
13	trigger button	16
14	PCle reset button	16
15	Flex cable inserting (left) / detaching (right)	17
16	XS-12P-X2G2-X8G3-SFF cable connection	18

List of Tables

1	Parameters and mass of XS-12P-X2G2-X8G3-SFF	Į
2	Connectors description	-
3	Flex connector description (24 pin)	8
4	Flex connector 24 pin assignment	{
5	Flex connector description (15 pin)	Ç
6	Flex connector 15 pin assignment	Ç
7	USB Type-A connector general description	1(
8	USB Type-A pin assignment	1(
9	Power connector description	1
10	Power connector pin assigment	1
11	10 connector general description	12
12	10 connector pin assigment	
13	DIP switch mode description	13
14	Digital trigger input ISO_GPI, signal levels	15
15	Digital output ISO_GPO_5VO, signal levels	1