

- **XS-12P-X2G2-X8G3-SFF**
Multi camera platform

XIMEA Accessories •
Technical Manual •
Version v250513 •

Introductions

About this manual

Dear customer,

Thank you for purchasing a product from XIMEA.

We hope that this manual can answer your questions, but should you have any further queries or if you wish to claim a service or warranty case, please contact your local dealer or refer to XIMEA Support on our website: www.ximea.com/support

The purpose of this document is to provide a description of XIMEA Accessories and to describe the correct way to install related software, drivers and run it successfully. Please read this manual thoroughly before operating your new XIMEA Accessories for the first time. Please follow all instructions and observe the warnings.

This document is subject to change without notice.

About XIMEA

XIMEA is one of the worldwide leaders for innovative camera solutions with a 30-year history of research, development and production of digital image acquisition systems. Based in Slovakia, Germany and the US, with a global distributor network, XIMEA offers their cameras worldwide. In close collaboration with customers XIMEA has developed a broad spectrum of technologies and cutting-edge, highly competitive products.

XIMEA's camera centric technology portfolio comprises a broad spectrum of digital technologies, from data interfaces such as USB 2.0, USB 3.1 and PCIe to cooled digital cameras with CCD, CMOS and sCMOS sensors, as well as X-ray cameras.

XIMEA has three divisions – generic machine vision and integrated vision systems, scientific imaging and OEM/custom.

Our broad portfolio of cameras includes thermally stabilized astronomy and x-ray cameras, as well as specialty cameras for medical applications, research, surveillance and defense.

Contact XIMEA

XIMEA is a worldwide operating company

Headquarters, Sales worldwide

XIMEA GmbH
Am Mittelhafen 16
48155 Münster
Germany

Tel: +49 (251) 202 408-0
Fax: +49 (251) 202 408-99

Web www.ximea.com
General inquiries info@ximea.com
Sales sales@ximea.com
Support [XIMEA Support](#)

Sales America

XIMEA Corp.
12600 W Colfax Ave., Suite A-130
Lakewood, CO 80215
USA

Tel: +1 (303) 389-9838
Fax: +1 (303) 202-6350

R&D, Production

XIMEA s.r.o.
Lesná 52
900 33 Marianka
Slovakia

Tel: +421 (2) 205 104 26
Fax: +421 (2) 205 104 27

Contents

About this manual	2
About XIMEA	2
Contact XIMEA	2
1 General description	4
2 Dimensional drawings	5
3 Configuration	6
3.1 DIP switches	6
4 Connectors	7
4.1 Location of connectors	7
4.2 Data interfaces	8
4.2.1 Flex cable connector (24 pin)	8
4.2.2 Flex cable connector (15 pin)	9
4.2.3 USB 3.1 Gen1 Type-A	10
4.2.4 Power connector	11
4.2.5 GPIO	11
5 Usages	12
5.1 Buttons	12
5.1.1 Trigger button	12
5.1.2 PCIe reset button	12
6 Additional information	13
7 Quickstart guide	14
7.1 Hardware setup	14
7.1.1 Essential components	14
7.1.2 Connecting the components	14
List of figures	15
List of tables	16

1 General description




Figure 1: Isometric view of XS-12P-X2G2-X8G3-SFF

The xiSwitch XS-12P-X2G2-X8G3-SFF is a multi-camera platform designed for high-performance synchronization of up to 12 cameras equipped with PCIe connectors from **xiX family**.

The xiSwitch XS-12P-X2G2-X8G3-SFF features:

- Device ports: 12x PCIe X2G2 Flex connectors with 10 Gbit bandwidth each for camera connections
- Device ports: 4x USB 3 X2G2 Flex connectors with 10 Gbit bandwidth each for camera connections
- 4x USB 3 Type-A connectors with 5 Gbit bandwidth
- Host ports: 2x PCIe x8 Gen3 SFF MiniSAS HD connectors with output bandwidth of 64 Gbit
- External power for reliable operation of connected cameras
- Communication, control, and synchronization through IO connector

The power supply operates with a DC voltage range of 12 to 24 V.

The xiSwitch XS-12P-X2G2-X8G3-SFF is designed for a wide range of applications, including:

360 panorama, Augmented or Virtual Reality (AR, VR), Autonomous self-driving vehicles, Street/city mapping, Deep learning tasks, Stereo camera systems, 3D scanning, Entertainment, Photogrammetry, FACS scanning, Face and Motion capture, UAV / UAS (drones), Cinematography, Videogrammetry and more.

2 Dimensional drawings




Figure 2: Dimensional drawing of XS-12P-X2G2-X8G3-SFF

Width [W]	Height [H]	Depth [D]	Mass [M]	Material and technology
140 mm	99.5 mm	38 mm	TBD	Extruded aluminum

Table 1: Parameters and mass of XS-12P-X2G2-X8G3-SFF

3 Configuration

3.1 DIP switches

The numbering of the camera ports correspond to the number of the respective GPI and GPO dip switches.

The DIP switches have annotation on their body. The description of DIP switches (GPI, GPO) is written directly on the PCB top layer.




Figure 3: XS-12P-X2G2-X8G3-SFF DIP switches

The switch to select the synchronization mode is in the left bottom area, next to the annotation “GPI Sel” with two possible states - “GPI” and “GPO_5V”.

4 Connectors

4.1 Location of connectors




Figure 4: Connectors location

Name	Description
USB-A 1-4	USB3 Type-A USB 3.0 (USB 3.1 Gen 1, Superspeed)
USB FL1-FL4	FPC/FFC USB Flex connectors
FL1-FL12	PCIe MX-X2G2 Flex connectors
IO	5-pin IO connector, 1843826
SFF A	PCIe iPass+ HD connector, SFF-8644, connector A
SFF B	PCIe iPass+ HD connector, SFF-8644, connector B
PWR	3-pin Power input connector, 1843800

Table 2: Connectors description

4.2 Data interfaces

4.2.1 Flex cable connector (24 pin)

Item	Value
Connector	Molex 502244-2430 (-FL), Molex 502231-2400 (-FV)
Signals	PCIe x2 Gen2, GND, IO
Mating Connectors	CBL-MX-X2G2-0M07 (-0M10,-0M25), CBL-PCIEFLEX-X2G2-0M10 (-0M25,-0M50)

Table 3: Flex connector description (24 pin)




Figure 5: Flex cable connector pinout

Pin	Name	GPI/GPO index API	Type
1	OUT1	-/1	Optically isolated Digital Output (OUT)
2	IN_OUT_GND	None	Common ground for opto-isolated IO
3	IN1	1/-	Optically isolated Digital Input (IN)
4	INOUT2	3/3	Non-isolated digital lines - Digital Input-Output (INOUT)
5	INOUT1	2/2	Non-isolated digital lines - Digital Input-Output (INOUT)
6	PWR	None	Power input
7	PWR	None	Power input
8	PCIe_RST0_N_IN	None	PCIe reset
9	GND	None	Ground return
10	PCIe_PERN_0	None	PCIe RX differential pair 0, neg.
11	PCIe_PERP_0	None	PCIe RX differential pair 0, pos.
12	GND	None	Ground return
13	PCIe_PERN_1	None	PCIe RX differential pair 1, neg.
14	PCIe_PERP_1	None	PCIe RX differential pair 1, pos.
15	GND	None	Ground return
16	PCIe_PETN_0	None	PCIe TX differential pair 0, neg.
17	PCIe_PETP_0	None	PCIe TX differential pair 0, pos.
18	GND	None	Ground return
19	PCIe_PETN_1	None	PCIe TX differential pair 1, neg.
20	PCIe_PETP_1	None	PCIe TX differential pair 1, pos.
21	GND	None	Ground return
22	PCIe_REFCLK_N	None	PCIe reference clock diff. pair, neg.
23	PCIe_REFCLK_P	None	PCIe reference clock diff. pair, pos.
24	GND	None	Ground return

Table 4: Flex connector 24 pin assignment

4.2.2 Flex cable connector (15 pin)

Item	Value
Connector	Molex 502244-15300 (-FL), Molex 502231-1500 (-FV)
Signals	USB 3.1 Gen1, IO, GND
Mating Connectors	CBL-MQ-FL-0M1, CBL-MQ-FL-0M25, CBL-USB3FLEX-0M10, CBL-USB3FLEX-0M25, CBL-USB3FLEX-0M50

Table 5: Flex connector description (15 pin)




Figure 6: Flex cable connector pinout

Pin	Name	GPI/GPO index API	Type
1	GND	None	Ground for pwr. and SuperSpeed signal return
2	SSRX-	None	SuperSpeed receiver differential pair
3	SSRX+	None	SuperSpeed receiver differential pair
4	GND	None	Ground for pwr. and SuperSpeed signal return
5	SSTX+	None	SuperSpeed transmitter differential pair
6	SSTX-	None	SuperSpeed transmitter differential pair
7	GND	None	Ground for pwr. and SuperSpeed signal return
8	D+	None	USB 2.0 differential pair
9	D-	None	USB 2.0 differential pair
10	GND	None	Ground for pwr. and SuperSpeed signal return
11	VBUS	None	Power input
12	VBUS	None	Power input
13	OUT1	-/1	Optically isolated Digital Output (OUT)
14	IN/OUT GND	None	Common pole (IO Ground)
15	IN1	1/-	Optically isolated Digital Input (IN)
Gnd. pins	SGND	None	Shield of FPC cbl. connected to shield of host controller

Table 6: Flex connector 15 pin assignment

4.2.3 USB 3.1 Gen1 Type-A

Item	Value
Connector	USB 3.1
Signals	Standard USB 3.1 Gen1 Type-A Connector
Mating Connectors	Standard USB 3.1 Type-A Connector

Table 7: USB Type-A connector general description




Figure 7: USB3 Type-A pinout

Pin	Signal	Description
1	VBUS	Power supply 5 V
2	D-	USB 2.0 differential data line neg.
3	D+	USB 2.0 differential data line pos.
4	GND	Ground return for power and signal
5	SSRX-	SuperSpeed receive differential pair neg.
6	SSRX+	SuperSpeed receive differential pair pos.
7	GND	Ground return for power and signal
8	SSTX-	SuperSpeed transmit differential pair neg.
9	SSTX+	SuperSpeed transmit differential pair pos.

Table 8: USB Type-A pin assignment

4.2.4 Power connector

Item	Value
Connector	CONN Header Block 3-POS, 3.5MM, Right Angle, 250V/8A, THT, 1843800
Signals	Power, GND
Mating connector	Phoenix Contact 1847068

Table 9: Power connector description




Figure 8: Power connector pinout

Pin	Name	Description
1	Vin 12 to 24 V	Power 12 to 24 V
2	SHLD	Shielding
3	GND	Power supply Ground

Table 10: Power connector pin assignment

4.2.5 GPIO

Item	Value
Connector	CONN Header Block 5-POS, 3.5MM, Right Angle, 250V/8A, THT, 1843826
Signals	IO, GND
Mating connector	Phoenix Contact 1847084 or 1863330

Table 11: IO connector general description



Figure 9: IO connector pinout

Pin	Name	Description
1	ISO_GPO	Open collector output from the selected “master” camera
2	ISO_GPO_5V	Push-pull 5 V output from the selected “master” camera
3	ISO_GND	(common) Isolated Ground for the IO subsystem
4	ISO_GPI	External input trigger signal, 3.3 to 24 V input
5	ISO_5V0	Isolated 5 V power output for IO subsystem ¹

¹Do not connect external power supply to this pin. Sourcing capability limited to 5 V 400 mA, including power needed for IO subsystem.

Table 12: IO connector pin assignment

5 Usages

5.1 Buttons

Two buttons are soldered on the multicamera platform.

5.1.1 Trigger button

This button can be used to generate a trigger pulse on the GPI-Selector output position to test the GPI configuration.

A rising edge trigger pulse (0 V -> 5 V) will be generated.




Figure 10: trigger button

5.1.2 PCIe reset button

Pressing this button will result in reset of the xiSwitch PCIe bus and all connected cameras.




Figure 11: PCIe reset button

Note: For debugging purposes only.

6 Additional information

Flex connectors are equipped with a locking mechanism. When locked, pulling the cable may lead to damage to the connector or the camera. When manipulating the cable, the power supply for the camera must be turned off.

Cables CBL-MQ-FL-xxx and CBL-MX-X2G2-xxxx have marked ends. It is important to connect the end marked "CAM" to the camera and the end marked "BOB" to the host or adapter (In this case to the xiSwitch XS-12P-X2G2-X8G3-SFF). Swapped orientation can cause damage to the camera.

Note: Flex cables PN: CBL-USB3FLEX-xxx or CBL-PCIEFLEX-X2G2-xxx are not polarized therefore the orientation of the cable between camera and host is not important.

Inserting Flex cable

- Step 1.** Open the lock on the connector.
- Step 2.** Insert the flex cable (e.g., CBL-MQ-FL-0M1) into the camera or xiSwitch.
- Step 3.** Close the connector lock.

Detaching Flex cable

- Step 1.** Open the lock on the connector.
- Step 2.** Gently pull the cable in the marked direction.
- Step 3.** Close the connector lock.




Figure 12: Flex cable inserting (left) / detaching (right)

7 Quickstart guide

7.1 Hardware setup

7.1.1 Essential components

It is important that the power is turned off when inserting/detaching the cables. General ESD precautions need to be applied. Failing this requirement may lead to camera and / or switch damage.

- XS-12P-X2G2-FF-X8G3-SFF multi camera platform
- Power cable: Cable with one DC power input socket female (OD5.5/ID2.1, Center +)
- Camera cables: e.g Firefly ECUE copper cable (CBL-ECUE-X4G3-xM0), USB Flex cable (CBL-USB3FLEX-0M10), PCIe Flex cable (CBL-MX-X2G2-0M25)
- XIMEA camera with PCIe FireFly, Flex or USB Flex interface
- Host cable: SFF-8644 cable (CBL-PCUO-SFF-cable)
- Host PC

7.1.2 Connecting the components

- Step 1.** Ensure the power supply and the computer are turned off before connecting any cables.
The order of cable connections is not strictly specified.
- Step 2.** After all other cables are connected, connect the XS-12P-X2G2-FF-X8G3-SFF to the power supply.
- Step 3.** Power on the computer.




Figure 13: XS-12P-X2G2-X8G3-SFF cable connection

For more information about XS-12P-X2G2-X8G3-SFF please contact: sales@ximea.com.

List of Figures

1	Isometric view of XS-12P-X2G2-X8G3-SFF.....	4
2	Dimensional drawing of XS-12P-X2G2-X8G3-SFF.....	5
3	XS-12P-X2G2-X8G3-SFF DIP switches.....	6
4	Connectors location.....	7
5	Flex cable connector pinout.....	8
6	Flex cable connector pinout.....	9
7	USB3 Type-A pinout.....	10
8	Power connector pinout.....	11
9	IO connector pinout.....	11
10	trigger button.....	12
11	PCIe reset button.....	12
12	Flex cable inserting (left) / detaching (right).....	13
13	XS-12P-X2G2-X8G3-SFF cable connection.....	14

List of Tables

1	Parameters and mass of XS-12P-X2G2-X8G3-SFF	5
2	Connectors description	7
3	Flex connector description (24 pin)	8
4	Flex connector 24 pin assignment	8
5	Flex connector description (15 pin)	9
6	Flex connector 15 pin assignment	9
7	USB Type-A connector general description	10
8	USB Type-A pin assignment	10
9	Power connector description	11
10	Power connector pin assignment	11
11	IO connector general description	11
12	IO connector pin assignment	11

PRELIMINARY

XIMEA GmbH

Am Mittelhafen 16 • 48155 Münster • Germany • www.ximea.com

© Copyright, XIMEA GmbH, All rights reserved