

XC-X4G3-MTP-X4G3-IPASS

MTP converter adapter

XIMEA Accessories

Technical Manual

Version v260828

Introductions

About this manual

Dear customer,

Thank you for purchasing a product from XIMEA.

We hope that this manual can answer your questions, but should you have any further queries or if you wish to claim a service or warranty case, please contact your local dealer or refer to XIMEA Support on our website: www.ximea.com/support

The purpose of this document is to provide a description of XIMEA Accessories and to describe the correct way to install related software, drivers and run it successfully. Please read this manual thoroughly before operating your new XIMEA Accessories for the first time. Please follow all instructions and observe the warnings.

This document is subject to change without notice.

About XIMEA

XIMEA is one of the worldwide leaders for innovative camera solutions with a 30-year history of research, development and production of digital image acquisition systems. Based in Slovakia, Germany and the US, with a global distributor network, XIMEA offers their cameras worldwide. In close collaboration with customers XIMEA has developed a broad spectrum of technologies and cutting-edge, highly competitive products.

XIMEA's camera centric technology portfolio comprises a broad spectrum of digital technologies, from data interfaces such as USB 2.0, USB 3.1 and PCIe to cooled digital cameras with CCD, CMOS and sCMOS sensors, as well as X-ray cameras.

XIMEA has three divisions – generic machine vision and integrated vision systems, scientific imaging and OEM/custom.

Our broad portfolio of cameras includes thermally stabilized astronomy and x-ray cameras, as well as specialty cameras for medical applications, research, surveillance and defense.

Contact XIMEA

XIMEA is a worldwide operating company

Headquarters, Sales worldwide	Sales America	R&D, Production
XIMEA GmbH Am Mittelhafen 16 48155 Münster Germany	XIMEA Corp. 12600 W Colfax Ave., Suite A-130 Lakewood, CO 80215 USA	XIMEA s.r.o. Lesná 52 900 33 Marianka Slovakia
Tel: +49 (251) 202 408-0 Fax: +49 (251) 202 408-99	Tel: +1 (303) 389-9838 Fax: +1 (303) 202-6350	Tel: +421 (2) 205 104 26 Fax: +421 (2) 205 104 27

Web	www.ximea.com
General inquiries	info@ximea.com
Sales	sales@ximea.com
Support	XIMEA Support

Contents

About this manual 2
About XIMEA 2
Contact XIMEA 2

1 General description 4

2 Dimensional drawings 5

3 Connectors 6
3.1 Location of connectors 6
3.2 Data interfaces 7
3.2.1 MTP optical fiber connector 7

4 Additional information 8
4.1 Cables 8
4.1.1 CBL-MTP-X4G3-FF-10M0 8
4.1.2 CBL-PCUO-X4G3-0M15 8

5 Quickstart guide 9
5.1 Hardware setup 9
5.1.1 Essential components 9
5.1.2 Connecting the components 9

List of figures 10

List of tables 11

1 General description




Figure 1: Isometric view of XC-X4G3-MTP-X4G3-IPASS

- PCIe Gen.3 x4 iPass to MTP converter
- Link Speed 32 Gb/s

Adapter converter for connection of iPass X4G2 camera to MTP fiber optics cable. The cage (XCable housing) has been designed with standard MTP 10 cm cable. The adapter features an integrated Samtec PCUO module. This allows for a high-speed connection to your PC using an optical MTP cable.

Can be used with High speed and high resolution xiB camera series and xSWITCH.

2 Dimensional drawings




Figure 2: Dimensional drawing of XC-X4G3-MTP-X4G3-IPASS

Width [W]	Height [H]	Depth [D]	Mass [M]
24 mm	114.9 mm	16.8 mm	52 g

Table 1: Mechanical parameters of XC-X4G3-MTP-X4G3-IPASS

3 Connectors

3.1 Location of connectors




Figure 3: XC-X4G3-MTP-X4G3-IPASS connectors location

Num.	C12onnector
1	MTP optical connector (X4G3)
2	IPASS PCIe connector plug (X4G3)

Table 2: Connectors description

3.2 Data interfaces

3.2.1 MTP optical fiber connector

The MTP connector on the backside adapter is a 12-fiber male MTP connector. For proper operation, use MTP cables with a 12-fiber female connector, such as CBL-MTP-X4G3-FF-xxxM0, see Section CBL-MTP-X4G3-FF-10M0.

Item	Value
Connector	MTP Male 12-fiber connector (see CBL-PCU0-X4G3-0M15)
Signals	PCIe Gen3 x4, RX lanes, TX lanes
Mating Connectors	US Conec MTP (Pinless) Female connector
Mating Cable	Ximea PN: CBL-MTP-X4G3-FF-5M0, CBL-MTP-X4G3-FF-10M0, CBL-MTP-X4G3-FF-20M0, CBL-MTP-X4G3-FF-30M0, CBL-MTP-X4G3-FF-53M0

Table 3: MTP connector general description




Figure 4: MTP connector pinout

Pin	Name	Description
1	Rx0	Receive channel 0
2	Rx1	Receive channel 1
3	Rx2	Receive channel 2
4	Rx3	Receive channel 3
5	NC	Not connected
6	NC	Not connected
7	NC	Not connected
8	NC	Not connected
9	Tx3	Transmit channel 3
10	Tx2	Transmit channel 2
11	Tx1	Transmit channel 1
12	Tx0	Transmit channel 0

Table 4: MTP connector pin assignment

4 Additional information

4.1 Cables

4.1.1 CBL-MTP-X4G3-FF-10M0

To connect product with MTP connector to MTP host connector you can use a 10-meter MTP fiber-optic trunk cable supporting PCIe Gen3 x4 with a data rate of 20 Gbit/s. It uses US Conec MTP® (pinless) female-to-female connectors and contains 12 Corning ClearCurve glass fibers. The cable features a minimum bend radius of 7.5 mm and a plenum (OFNP)-rated outer jacket.

It is also available in 5 m, 20 m, 30 m, and 53 m lengths.




Figure 5: CBL-MTP-X4G3-FF-10M0 cable

4.1.2 CBL-PCUO-X4G3-0M15

The product includes the CBL-PCUO-X4G3-0M15, a 15 cm MTP to Firefly 12-fiber cable supporting PCIe Gen3 x4.




Figure 6: CBL-PCUO-X4G3-0M15 cable

5 Quickstart guide

5.1 Hardware setup

5.1.1 Essential components

It is important that the power is turned off when inserting/detaching the cables. General ESD precautions need to be applied. Failing this requirement may lead to product damage.

- a camera
- host PC
- adapter (XC-X4G3-MTP-X4G3-IPASS)
- host adapter
- MTP fiber optic cables (e.g. CBL-MTP-X4G3-FF-10M0)

5.1.2 Connecting the components

This accessory can be used as an end-connecting component for the camera as well as an end-connecting component for the computer (see Step 3. and Step 4., Options A / B below).

Step 1. Ensure the PC is turned off and unplugged from the power source and then deploy the host adapter to the PC

Step 2. Connect the MTP cable to the XC-X4G3-MTP-X4G3-IPASS adapter

Step 3. Option A: Connect the MTP cable to the computer
Option B: Connect the MTP cable to the connected device (e.g., the camera)

Step 4. Option A: Connect the PCIe side of the adapter to the connected device (e.g., the camera)
Option B: Connect the PCIe side of the adapter to the computer

Step 5. Power up the PC




Figure 7: Connecting steps

For more information about XC-X4G3-MTP-X4G3-IPASS please contact: sales@ximea.com.

List of Figures

1 Isometric view of XC-X4G3-MTP-X4G3-IPASS 4
2 Dimensional drawing of XC-X4G3-MTP-X4G3-IPASS 5
3 XC-X4G3-MTP-X4G3-IPASS connectors location 6
4 MTP connector pinout 7
5 CBL-MTP-X4G3-FF-10M0 cable 8
6 CBL-PCUO-X4G3-0M15 cable 8
7 Connecting steps 9

List of Tables

1 Mechanical parameters of XC-X4G3-MTP-X4G3-IPASS 5
2 Connectors description 6
3 MTP connector general description 7
4 MTP connector pin assignment 7

XIMEA GmbH
Am Mittelhafen 16 • 48155 Münster • Germany • www.ximea.com
© Copyright, XIMEA GmbH, All rights reserved